

Compact single outlet, quadrangular Assembly instruction



Compact single outlet, quadrangular

Assembly instruction



Quadrangular compact single outlet, external dimensions 125 x 125 mm and 160 x 160 mm for installation directly into screed, suitable for dry and wet maintenance rooms. Scope of delivery contains floor box, stainless steel unit and shuttering unit. For parquet and stone floors of 12/22 mm levelling range: 80–125 mm or 90–135 mm.



1 | Floor box Align floor box in dead centre as delivered. Bend open ears and fix to raw ceiling.



2 | Plastic conduit Bend open perforation in the sides of floor box and insert plastic conduit.



3 | Casting screed Seal all openings of the floor box as delivered and cast screed accurately to the shuttering unit. Remove shuttering unit when screed is hardened.



4 | Levelling to floor Remove cartridge cover and rubber seal and adjust single outlet to floor height flush over the four levelling screws.



5 | Data systems Insert connected data jacks from below into the plate. Fasten equipped plate at the side of the single outlet.



6 | Heavy current systems Insert heavy current devices from the top and connect from below. Insert equipped plate using the snap tabs into the frame and fasten the opposite side.

Compact single outlet, quadrangular Assembly instruction



7 | Assembly Insert heavy current and low current plugs.



8 | Single outlet Insert rubber seal and cartridge cover. In case of dry maintenance floors install cartridge unit with cable outlet. Comply with potential equalization.



9 | Installation devices Latch sockets and data devices into plate and connect conducts.



10 | Single outlet frame Fasten equipped plates to single outlet frame.



11 Assembly Insert heavy current and low current plugs.



12 | Tube Insert rubber seal and tube cover. In case of wet maintenance floors, mount single tube outlet and tube. Comply with potential equalization.



Errors and technical modification subject to change, reproduction as well as electronic duplication only with our written permission. With appearance of this print all preceding documents lose their validity.



www.puk.com

© PUK Group | PUK-MA UFS-UKE EN | WEST | x | 2016-04-15